

## Tech Tips

### DVA-5205P or DHA-S680P Setup

Some factory settings of DVA-5205P or DHA-S680P may not be compatible with your system configuration. If you have no Audio after installing DVA-5205P from any source like CD-Changer please follow the setup instructions "Custom Setup".

To go to the DVA-5205P or DHA-S680P setup Menu, follow the following procedure:

Play a video in the DVA-5205P or DHA-S680P and be sure that you can control it by the remote controller RUE-4168



Press STOP on the RUE-4168. A **PRE-STOP** will appear on the screen.



Press again STOP and a **STOP** will appear on the screen.



Press and hold the MENU / SET key on the remote control until the main setup menu will appear on the screen.

### Main Setup screen



You can click directly on the screen on the right to go to the menu point description.

### Language selection

In the languages menu, you can Pre-define your preferred languages for Audio, Subtitle and Menu of any inserted DVD. This function is not supported by all DVD's.



#### Video output mode (4:3 / 16:9)

Select **LETTERBOX** when connected to a conventional 4:3 size monitor. There may be black stripes visible at the top and bottom of the screen. Select **PAN-SCAN** when connected to a conventional 4:3 size monitor. The picture will fill the entire TV screen. However, due to the mismatch in aspect ratio, parts of the movie at the extreme left and right sides will not be visible.



Select **16:9** if the DVA-5205P or DHA-S680P is connected to a 16:9 Monitor such as IVA-C800R or TME-M750.

#### Parental Locking

You should not try to switch the country code of your DVA-5205P or DHA-S680P. This Country code is only for the function "Rating Level".



For more information on Country code and Rating Level you can Download [here](#) the owners manual of DVA-5205P.

#### DVD-Audio down sampling

##### ON:

The digital signals recorded on the Audio DVD disc with 96 kHz/24bit, 48 kHz/24bit, 48kHz/20bit sampling are converted into digital signals with 48kHz/16bits sampling for output from the optical cable. Set to ON at time of shipment from factory.

##### OFF:

The digital signals recorded on the DVD disc with 96 kHz/24bit, 48 kHz/24bit, 48kHz/20bit sampling are not converted into digital signals with 48 kHz/16bits sampling. They are not output from the optical cable.



#### Audio out with non-Dolby Digital Processor

**AUTO:**

The digital output is switched automatically according to the type of audio signals being played. Be sure to select "AUTO" when you want to connect a digital audio processor and play Dolby Digital audio. "AUTO" is selected upon shipment from the factory.



**LPCM:**

The audio signals recorded on the disc are converted into 44,1 kHz/16 bit linear PCM audio signals for output. Select LPCM when you want to connect other processors than PXA-H510 or PXA-H900.

**Led Indicator**

**ON:**

The LED indicators are lit, indicating the product's operating status. "ON" is selected upon shipment from the factory.



**OFF:**

The LED indicators are turned off. When "OFF" is set, the indicators do not light even when the power is on.

**Custom Setup / Closed Caption**

DVD includes so-called "closed captions" which describe the scene to persons with impaired hearing. It is possible to turn the closed captions ON and OFF.



**ON:**

Displays the closed captions.

**OFF:**

Does not display the closed captions. Set to OFF at time of shipment from factory.

**Custom Setup / AI-Net Setup**

**DVD:**

Set to "DVD" when connected to the CVA-1005R/ IVA-M700R/ IVA-C800R/ CDA-7990R/ CDA-7969R.

Operations can be performed using the CVA-1005R/ IVA-M700R/ IVA-C800R's main menu screen, or the CD-Tuner's keys. "DVD" is selected upon shipment from the factory.



**CD:**

Set to "CD" when connected to an Ai-NET product (head unit) other than the above (for ex.: CVA-1000R).

Operations can partly be performed from the head unit.

**Custom Setup / H.U. Control**

**ON:**

Possible to operate from an full Ai-NET compatible head unit or an Ai-NET compatible AV head unit (CDA-7990R/ CDA-7969R/ CVA-1005R/ IVA-M700R/ IVA-C800R).

**OFF:**

Not possible to operate from an Ai-NET compatible head unit or an Ai-NET compatible AV head unit. Set to OFF at time of shipment from factory.



**Switch between NTSC and PAL**

If you see this picture when you insert a DVD in the DVA-5205P or DHA-S680P you are inserting either a NTSC DVD or the DVD-Player is currently set to NTSC. You can switch between NTSC and PAL by holding the power button of the Remote controller. Of course you can not change the regional code of DVA-5205P or DHA-S680P.

